



# Restaurant Max Inc.

4775 Mendel Court, sw. Bldg A, Atlanta, GA 30336 - 404-472-0398 (Fax) 404-472-0399  
 Hinge Kit for Roof Mount Commercial Fans

## Typical Hinge Kit

**HINGE KIT INSTALLATION**

**CLOSED POSITION**

**OPEN POSITION**

**ATTENTION!**  
 INSTALLER MUST READ LABEL NEAR DISCONNECT SWITCH MESSAGE ON LABEL. \*INSTALLER SHOULD SUPPLY CORRECT ELECTRICAL CORD TO LEFT FAN BASE COMPLETE SWING\*

**PARTS INCLUDED**

- 2 - FAN PLATES (LEFT & RIGHT)
- 2 - CURB PLATES (LEFT & RIGHT)
- 2 - WHEZ BELTS
- 6 - WHEZ NUTS
- 4-SHEET METAL SCREWS
- 12 - SHORT 3/8" LG.
- 12 - LONG 3/4" LG.

**HINGE KIT FIELD INSTALLATION**

**STEP 1)**  
 ASSEMBLE FAN PLATE WITH CURB PLATE AS SHOWN ON FIG. 1 AND FIG. 2 (IF PARTS ARE NOT ASSEMBLED).

**STEP 2)**  
 SEE DETAIL "A" FOR POSITIONING FAN PLATE ON FAN BASE. LINE UP FAN BASE EDGE TO INSIDE EDGE OF FAN PLATE AS SHOWN ON FIG. 3.

**STEP 3)**  
 SCREW THE FAN PLATE TO THE FAN BASE USING THE (12) SHORT 3/8" LG. SHEET METAL SCREWS. NOTE: IF THE SCREWS HIT THE CURB, THEN RUN THE SCREWS FROM INSIDE THE FAN BASE, ALWAYS BE SURE THAT SCREWS DO NOT INTERFERE WITH CURB WHEN FAN SWINGS (SEE FIG. 4).

**STEP 4)**  
 SCREW THE CURB PLATE TO THE CURB USING THE (12) LONG 3/4" LG. SHEET METAL SCREWS. TIGHTEN NUT AND BOLT ASSEMBLY, ENSURE FAN SWINGS PROPERLY.

## Typical Grease Box Installation

**GREASE BOX INSTALLATION**

**CLOSED POSITION**

**OPEN POSITION**

**PARTS INCLUDED**

- GREASE BOX
- GREASE BOX COVER
- GREASE PIPE
- SHEET METAL SCREWS
- 3 - LONG (3/4" LG)

**GREASE BOX FIELD INSTALLATION**

**STEP 1)**  
 ATTACH GREASE BOX COVER TO THE CURB, HOLD 3" DIMENSION AS SHOWN ON FIG. 1. SCREW GREASE BOX COVER TO CURB USING (3) LONG (3/4" LG) SCREWS AS SHOWN ON FIG. 2.

**STEP 2)**  
 ATTACH GREASE BOX TO GREASE BOX COVER, SLID AND SHOP AS SHOWN ON FIG. 3.

**STEP 3)**  
 INSTALL GREASE PIPE AS SHOWN ON FIG. 4.